







One-On-One™ Direct Replacement Motors

	MARS NO.	MFG. NO	HP	VOLTS	RPM/SPEEDS	ROT	AMPS	DIMENSIONS		
								A	B	C
Carrier (con't)										
	D455	-	1/30	115 / 230	3000/1	CCW SE	1.3 - .7	3.88	5.88	-
	Shaded pole, ball bearing, includes shaft bushing, 1/4 inch dia. shaft									
	Replaces: Draft Booster/Flue Exhaust Switch Motors									
	D456	-	1/15	115 / 230	3000/1	CW SE	2.0-1.0	2.75	6.50	-
	Shaded pole, ball bearing, includes shaft bushing, 1/4 inch dia. shaft									
	Replaces: Draft Booster/Flue Exhaust Switch Motors									
	D457	-	1/15	115 / 230	3000/1	CCW SE	2.0-1.0	2.75	6.50	-
	Shaded pole, ball bearing, includes shaft bushing, 1/4 inch dia. shaft									
	Replaces: Draft Booster/Flue Exhaust Switch Motors									
	D458	-	1/15	208 - 230	3000/1	CW SE	1.0	2.75	6.50	-
	Shaded pole, ball bearing, includes shaft bushing, 1/4 inch dia. shaft									
	Replaces: Draft Booster/Flue Exhaust Switch Motors									
	D1174	-	1/15	460	3000/1	CW SE	0.6	2.50	6.75	-
	Shaded pole, ball bearing, does not have shaft bushing, 1/4 inch dia. shaft									
	Replaces: Carrier HC34AU725A, Universal JB1P044NV, HC24AU725									
	D1178	-	40193	208 - 230	3450/1	CW SE	0.5	2.75	6.75	-
	PSC, ball bearing, 1/4 inch dia. shaft									
	Replaces: Carrier HC680001, Fasco 7162-3829									

ONE-ON-ONE